

Sure Cross® Temperature and Humidity Sensor



Datasheet



The Sure Cross® Temperature and Humidity Sensor works in a variety of environments to provide temperature and humidity measurements.

- Manufactured with a robust metal housing
- Functions as a Modbus slave device via RS-485
- Ships with aluminum grill filter cap; optional stainless steel 10 micrometer sintered filter available separately



WARNING: Not To Be Used for Personnel Protection

Never use this device as a sensing device for personnel **protection**. Doing so could lead to serious injury or death. This device does not include the self-checking redundant circuitry necessary to allow its use in personnel safety applications. A sensor failure or malfunction can cause either an energized or de-energized sensor output condition.

For additional information, updated documentation, and a list of accessories, refer to Banner Engineering's website, www.bannerengineering.com/wireless.

Configure this sensor using the [Sensor Configuration Tool](#) and adapter cable BWA-HW-006 (datasheet [140377](#)).

Banner Humidity Sensor Calibration Statement. This calibration statement (also available online) lists the chain with which the calibration of Banner humidity sensors is traceable to NIST standards. A Certificate of Factory Calibration ships with every temperature/humidity or temperature sensor. Although your certificate will be specific to your product, a sample certificate is available for [download](#).


Models

Models	Power Requirements	I/O
M12FTH3Q	3.6 to 5.5 V dc low power option or 12 to 24 V dc	Temperature and relative humidity via RS-485 Modbus
M12FT3Q		Temperature via RS-485 Modbus

Connecting the Temperature/Humidity Sensor

To install the sensor to a device with a 5-pin Euro-style female end, follow these instructions:

1. Align the notch in the female connector with the key in the sensor's male connector.
2. Gently slide the sensor end into the connector.
3. Rotate the threaded nut to tighten the sensor down. **DO NOT** attempt to rotate the sensor after it is connected to the device or the cable end because this will damage the sensor.



Wiring

5-pin M12/Euro-style Male Connector	Pin	Wire Color	Sensor Connection
	1	Brown	Power IN (+). Either 3.6–5.5 V dc (Low Power Mode) or 12–24 V dc
	2	White	RS485 / D1 / B / +
	3	Blue	Ground (-)
	4	Black	RS485 / D0 / A / -



5-pin M12/Euro-style Male Connector	Pin	Wire Color	Sensor Connection
	5	Gray	For 12–24 V dc operation: Not Used For 3.6–5.5 V dc operation: Discrete NPN Select Line. Pull to ground to enable serial communications; release from ground to disable serial communications

Refer to the Class I Division 2 control drawings (p/n [143086](#)) for wiring specifications or limitations.

Low Power Mode operation (3.6–5.5 V dc operating voltage) offers the user savings in power consumption by putting the Banner Temperature and Humidity Sensor's serial communications to sleep whenever the sensor is deselected. Low Power Mode operation is ideal for battery-powered applications or any application with power consumption restrictions. When the sensor is deselected, power consumption drops to 45 µA. When the sensor is selected, power consumption is 4 mA.

To operate the Banner Temperature and Humidity Sensor in Low Power Mode, the supply voltage applied to Power In must be within the range of 3.6–5.5 V dc. Set the Select Line to 0 V (ground) to select the sensor and activate the sensor's serial communications. Release the Select Line from 0 V (ground) to deselect the sensor and disable the sensor's serial communications. When deselected, the sensor's green LED continues to blink normally. To bypass Low Power Mode, connect the Select Line to ground (0 V).

For example, to use Low Power Mode, use 3.6 V dc battery power and connect the Select Line to Discrete Output 1 (NMOS output, low active).

Modbus Registers

Sensor Address	Description	I/O Range		Holding Register Representation	
		Min Value	Max Value	Min (Dec)	Max (Dec)
40001	Humidity (%RH) ¹	0	100.00%	0	10,000
40002	Temperature (°C)	-1638.4	1638.3	-32768	32767
40003	Temperature (°F)	-1638.4	1638.3	-32768	32767
46101	Baud	0=9.6k, 1=19.2k (default), 2=38.4k			
46102	Parity	0=none (default), 1=odd, 2=even			
46103	Modbus slave address	1 (default) through 247			

The temperature = (Modbus register value) ÷ 20.

Specifications

Supply Voltage

12 to 24 V dc OR 3.6 to 5.5 V dc low power option

Current

Default sensing: 45 µAmps
Disabled sensing: 32 µAmps
Active comms: 4 mA

Discrete Input

One, NPN/Sinking
Rating: 3 mA max current at 30 V dc
Sample Rate: 125 milliseconds
ON Condition (NPN): Less than 0.7 V
OFF Condition (NPN): Greater than 2 V or open

Temperature

Measuring Range: -40 °C to +85 °C (-40 °F to +185 °F)²
Resolution: 0.1 °C
Accuracy
-40 °C to 0 °C: ± 0.6 °C
0 °C to 60 °C: ± 0.4 °C
+60 °C to +85 °C: ± 1.2 °C

Operating the Modbus temperature/humidity sensor at voltages greater than 12 V can increase the temperature accuracy error by up to 1 °C. The amount of error depends upon the application's device mounting and air flow characteristics.

Mounting Threads

M12 × 1

Indicators

Green flashing: Power ON
Red flicker: Serial Tx

Temperature and/or Humidity Input

Sample Rate: 16 seconds

Communication

Interface: RS-485 serial
Baud rates: 9.6k, 19.2k (default), or 38.4k
Data format: 8 data bits, no parity (default), 1 stop bit (even or odd parity available)
Do not use termination resistor.
Protocol: Modbus RTU

Humidity³

Measuring Range: 0 to 100% relative humidity
Resolution: 0.1% relative humidity
Accuracy:
25 °C: ±2%
0 °C to 70 °C and 10–90%: ±3%
0 °C to 70 °C and 0–10 % or 90–100 %: ± 7%

¹ Only available on the M12FTH3Q model. Humidity sensor is not included with the M12FT3Q model.

² Operating the devices at the maximum operating conditions for extended periods can shorten the life of the device.

³ Humidity measurements are only available with model M12FTH3Q. Model M12FT3Q does not include the humidity sensor.

Environmental Rating
IEC IP67; NEMA 6

Operating Temperature
-40 °C to +85 °C (-40 °F to +185 °F)

Shock and Vibration
IEC 68-2-6 and IEC 68-2-27
Shock: 30g, 11 millisecond half sine wave, 18 shocks
Vibration: 0.5 mm p-p, 10 to 60 Hz

Certifications



CSA: Class I, Division 2, Groups A, B, C, D — Certificate 1921239

Refer to the Class I Division 2 control drawings (p/n 143086) for wiring specifications or limitations. All battery-powered devices must only use the lithium battery manufactured by Xeno, model XL-205F.

Accessories

Temperature-Humidity Filter Caps

FTH-FIL-001

- Aluminum grill filter cap (factory default, ships with M12FT*Q sensors)



FTH-FIL-002

- Stainless steel, sintered to 10 micrometer porosity (for high dust environments.)



5-Pin Euro-Style Cordsets

5-Pin Threaded M12/Euro-Style Cordsets—Single Ended				
Model	Length	Style	Dimensions	Pinout (Female)
MQDC1-501.5	0.50 m (1.5 ft)	Straight		<p>1 = Brown 2 = White 3 = Blue 4 = Black 5 = Gray</p>
MQDC1-506	1.83 m (6 ft)			
MQDC1-515	4.57 m (15 ft)			
MQDC1-530	9.14 m (30 ft)			
MQDC1-506RA	1.83 m (6 ft)	Right-Angle		
MQDC1-515RA	4.57 m (15 ft)			
MQDC1-530RA	9.14 m (30 ft)			

Banner Engineering Corp. Limited Warranty

Banner Engineering Corp. warrants its products to be free from defects in material and workmanship for one year following the date of shipment. Banner Engineering Corp. will repair or replace, free of charge, any product of its manufacture which, at the time it is returned to the factory, is found to have been defective during the warranty period. This warranty does not cover damage or liability for misuse, abuse, or the improper application or installation of the Banner product.

THIS LIMITED WARRANTY IS EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES WHETHER EXPRESS OR IMPLIED (INCLUDING, WITHOUT LIMITATION, ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE), AND WHETHER ARISING UNDER COURSE OF PERFORMANCE, COURSE OF DEALING OR TRADE USAGE.

This Warranty is exclusive and limited to repair or, at the discretion of Banner Engineering Corp., replacement. IN NO EVENT SHALL BANNER ENGINEERING CORP. BE LIABLE TO BUYER OR ANY OTHER PERSON OR ENTITY FOR ANY EXTRA COSTS, EXPENSES, LOSSES, LOSS OF PROFITS, OR ANY INCIDENTAL, CONSEQUENTIAL OR SPECIAL DAMAGES RESULTING FROM ANY PRODUCT DEFECT OR FROM THE USE OR INABILITY TO USE THE PRODUCT, WHETHER ARISING IN CONTRACT OR WARRANTY, STATUTE, TORT, STRICT LIABILITY, NEGLIGENCE, OR OTHERWISE.

Banner Engineering Corp. reserves the right to change, modify or improve the design of the product without assuming any obligations or liabilities relating to any product previously manufactured by Banner Engineering Corp. Any misuse, abuse, or improper application or installation of this product or use of the product for personal protection applications when the product is identified as not intended for such purposes will void the product warranty. Any modifications to this product without prior express approval by Banner Engineering Corp will void the product warranties. All specifications published in this document are subject to change. Banner reserves the right to modify product specifications or update documentation at any time. Specifications and product information in English supersede that which is provided in any other language. For the most recent version of any documentation, refer to:

www.bannerengineering.com